



#### **OPERATING INSTRUCTIONS - CL500**

1. INSTALL REFLECTOR ("PHOTOGENIC" WITH QUICK CHANGE RING) BY SQUEEZING QUICK RELEASE TABS WHILE INSERTING TOP EDGE OF REFLECTOR QUICK RELEASE RING INTO QUICK CHANGE HOUSING.
2. INSTALL LAMP (500 WATT MAXIMUM WITH MEDIUM HOUSEHOLD SCREW BASE), FOLLOWING LAMP MANUFACTURER'S SAFETY & HANDLING INSTRUCTIONS.
3. MOUNT THE LIGHT UNIT ON A HEAVY DUTY STAND. USE THE APPROPRIATE STAND ADAPTER BUSHING (SUPPLIED WITH THE LIGHT) FOR 1/2" OR 3/8" STAND TOPS. NO BUSHING IS REQUIRED WITH A 5/8" STAND TOP.
4. SWITCH LIGHT ON.
5. REVERSE THE PROCEDURE OUTLINED IN ITEMS 1, 2, & 3 TO BREAK UNIT DOWN FOR STORAGE OR TRANSPORT. ALLOW FOR COOLING TIME OF AT LEAST 15 MINUTES.
6. USE ONLY WITH CIRCUIT BREAKER PROTECTED ELECTRICAL OUTLETS. IF CIRCUIT BREAKER TRIPS, CHECK FOR CIRCUIT OVERLOAD AND DISCONNECT OTHER ELECTRICAL EQUIPMENT AS NEEDED SO THAT THE TOTAL AMP DRAW ON THE CIRCUIT IS LOWER THAN THE RATING OF THE CIRCUIT BREAKER.

## Photogenic Professional Lighting

### ASSEMBLY & OPERATING INSTRUCTIONS - CL500



#### **GENERAL HAZARD WARNING:**

FAILURE TO COMPLY WITH THE PRECAUTIONS AND INSTRUCTIONS PROVIDED WITH THIS LIGHT UNIT CAN RESULT IN DEATH, SERIOUS BODILY INJURY, AND PROPERTY LOSS OR DAMAGE FROM HAZARDS OF FIRE, EXPLOSION, BURN, OR ELECTRICAL SHOCK.

ONLY PERSONS WHO CAN UNDERSTAND AND FOLLOW THE INSTRUCTIONS SHOULD USE THIS LIGHT UNIT.

THIS LIGHT UNIT IS DESIGNED FOR PROFESSIONAL USE ONLY. IT SHOULD NEVER BE USED FOR PURPOSES OTHER THAN PROFESSIONAL PHOTOGRAPHY.



#### **WARNING:**

NOT FOR HOME OR RECREATIONAL USE.



#### **WARNING:**

FIRE, BURN AND EXPLOSION HAZARD. KEEP COMBUSTIBLE MATERIALS SUCH AS PAPER, WOOD, OR CLOTH AT LEAST 6 FEET FROM THE FRONT AND AWAY FROM THE SIDES AND REAR OF THIS LIGHT. NEVER USE THIS LIGHT IN AREAS WHICH MAY CONTAIN VOLATILE OR AIRBORNE COMBUSTIBLES OR PRODUCTS SUCH AS GASOLINE, SOLVENT, PAINT THINNER OR UNKNOWN CHEMICALS.



#### **WARNING:**

##### **ELECTRICAL SHOCK HAZARD.**

**DO NOT** INSERT OBJECTS THROUGH THE FAN GRILL OR AROUND THE LAMP SOCKET. DO NOT PLACE THE LIGHT NEAR WET OR DAMP AREAS. THE CORD MUST BE UNPLUGGED WHEN CLEANING THE UNIT OR CHANGING THE LAMP.

#### **SAFETY PRECAUTIONS:**

1. CHECK THIS LIGHT UNIT THOROUGHLY FOR DAMAGE.
2. **DO NOT** OPERATE A DAMAGED LIGHT UNIT.
3. OPERATE ONLY ON A STABLE, LEVEL SURFACE.
4. USE ONLY HEAVY DUTY LIGHT STANDS WITH 3/8", 1/2", OR 5/8" PHOTOGRAPHIC INDUSTRY STANDARD STAND TOPS.
5. AVOID LOOKING DIRECTLY INTO THE LIGHT.
6. USE CAUTION WHEN MAKING LIGHT ADJUSTMENTS. THE LIGHT CAN DEVELOP VERY HOT SURFACES; PARTICULARLY ON THOSE SURFACES CLOSEST TO THE LAMP.
7. NEVER OPERATE THE LIGHT WITHOUT A REFLECTOR. THE REFLECTOR MUST BE LARGE ENOUGH SO THAT THE LAMP IS INACCESSIBLE FROM THE SIDES.
8. ALLOW THE LIGHT UNIT TO COOL FOR AT LEAST 15 MINUTES AFTER IT IS SWITCHED OFF.
9. ALWAYS UNPLUG THE LIGHT IF IT IS NOT BEING USED.
10. SECURE POWER CORD SUCH THAT THE LIGHT CANNOT BE PULLED OVER BY THE CORD.
11. DO NOT USE AN EXTENSION CORD UNLESS IT IS RATED FOR 5 AMPS OR MORE.
12. IF PLUG GETS HOT, CHECK CONDITION OF WALL OUTLET.
13. NEVER OPERATE THE LIGHT UNIT IF THE COOLING FAN BLADES ARE NOT RUNNING.
14. SWITCH THE LIGHT UNIT OFF IMMEDIATELY IF SMOKE OR FUMES ARE DETECTED.